

YORPOWER

YP9900PE







ENGINE FEATURES



Energy saving tech to reduce oil consumption




With freq conversion tech. Power output is strong and stable

Engine Oil Warning System Auto engine shut off for low oil level

Electric Start One click electric start

Function Indicator



GENERATOR FEATURES















ADDITIONAL INFORMATION

- Voltage range is within +-2%
- Frequency is within -1% / + 3% on full load
- Our optional 5 Display LED Screen allows you to view Voltage, Amps, KW, HZ and Hours all from one screen.
- Our optional Trolly Kit allows for easy maneuverability and transportation
- Comes with a relay to protect the battery charger from high temperatures









YORPOWER PETROL GENERATOR

Genset Model:

YP9900PE



Prime Power	6.2 kw	Phase	
Standby Power	6.8 kw	Cooling System	A
Frequency	50Hz	Fuel tank capacity	
Power Factor	1.0	Fuel type	
Voltage (VAC)	230V	Noise @7M	7
Voltage Regulator	By AVR	Dimension (LxWxH)	686 x
Fuel consumption (100% load)	3.1 L/hr	Gross Weight	
AC Output	230V x 2 Blue Euro Sockets	DC Output	12V,

Single				
Air-Cooled				
25 Litres				
Petrol				
78 db(A)				
686 x 516 x 560 mm				
88.5kg				
12V, 100W (8.3A)				

Engine: YORPOWER, Model: YP200

Type	4 Stroke	Fuel	Petrol
Number of cylinder	Single	Rotational speed	3,000 rpm
Displacement	420 cc	Starting system	Electric (and recoil)
Cooling system	Air-cooled	Oil capactity	1.1 Litre
Horsepower	15 HP	Compression ratio	8: 5: 1

Alternator: YORPOWER, Model: YP425-M01

Phase	Single	Voltage Regulator	By AVR
Rating	IP23 - H Class insulation	Alternator Coil	100% Copper coil

Protection system:

- Oil alert system: Low lubrication oil pressure
- (Breaker) overload protection

Other standards:

- Having anti-vibration system between transmitter with surrounding frame.
- Battery. 01 unit

Unit 2, Hurricane Close, Sherburn in Elmet, Leeds, LS25 6PB, United Kingdom +44 1977 688155 • sales@yorpower.com

www.yorpower.com